


MODEL #:	
UPC #::	

Linear High Bay



Model	Watts	Lumens	Volts	Color Temp.
30,000 Lumen P	ackage			
ORHB30L4K	215	28,390	120-277	4000K
ORHB30L5K	215	27,364	120-277	5000K

Photometrics



Light Loss Factor	1.00	
Total Lumens	28,390	
Mounting Height	20'	
Max. Calculated Value	31.79Fc	

Specifications

Electrical Specifications

- Input Wattage: 215
- · Efficacy: up to 132 LpW
- AC Input: 120/208/240/277 V
- Driver: Constant current, Class 2, 120-277VAC 50/60Hz
- Operating Temperature -40°C to +50°C (-40°F to +122°F)
- Dimming: 0-10V

Lighting Specifications

- Total Lumens: 27,364 28,390Color Temperature: 4000K | 5000K
- Color Rendering Index: 80

Housing Specifications

- High quality compact 2ft steel construction with white paint-after-fabrication finish
- · Color: White
- Lifespan: 50,000 hours

Lens

- Acrylic resin lens
- Frosted lens design for maximum light output

Installation

 Standard 3' chain mount and V hooks included

Listings

- UL/cUL standards for damp locations
- DesignLights Consortium qualified luminaire, eligible for rebates from DLC member utilities.

Model	DLC Prod. ID	Model	DLC Prod. ID
ORHB30L4K	P0A6Z0YR	ORHB30L4K	PQC1S82K

Warranty

5-Year limited warranty




MODEL #: ______

Linear High Bay

Dimensions


Product Dimensions

ORHB30L Weight: 9.1 lbs.




Carton Dimensions

ORHB30L Carton Weight: 22.1 lbs. 2 Units per Carton



Pallet Dimensions



Installation

Cautions:

- 1. Can not use the electric generator to test the LED lamp.
- 2. Please abide by related country, regional and local law and regulations when install this fixture.
- 3. Please turn off the power before installation or maintenance.
- 4. Proper earth grounding is required to ensure safety.

Notice:

- 1. To avoid possibility of electrical shock or fire, the installation personnel must have professional electric knowledge.
- 2. Please wear gloves to avoid injury before installation.
- 3. If any smoke or spark of the wire happened, please turn off the power immediately and notify relevant personnel.
- 4. Please use listed strain relief bushing when connection the supply cord to the outlet box.

Attention:

- 1. Please check if there is any damage during shipping. If so, please contact manufacturer timely.
- 2. Please read the installation instruction carefully to check whether all the accessories are complete. After confirmation, then install the fixture according to installation steps.

Wiring Diagram & Instruction:

- 3 dimming functions are available in this high bay light:
 - 1. Constant current can be achieved by 0-10VDC dimming;
 - 2. PWM signal dimming;

Two wiring method:

- 1. Conduit connection,
- 2.Flexible cord for connection.

Wiring Instruction

L:Black N:White

(a): Green/Yellow DIM + : Purple

DIM - : Grey

Wiring Instruction

